

**Iron Core Ballasts**

CODE	Type	Current draw	Wattage	Watts loss
B468W	EC4-6-8	165ma	4, 6, 8	4_5
B9W	EC9	165ma	9	2.5
B10W	EC10	225ma	10	7
B13W	EC13	215ma	13	3.9
B13WSlimline	SL13	n/a	13	
B15W	EC15	310ma	15	9
B18 20W	EC18-20	370ma	18-20	10.3
B30W	EC30	360ma	30	15
B36 40W	EC36-40	415ma	36-40	10
B58 65W	EC58-65	660ma	58-65	13
B75W	EC75	640ma	75	
80W	EC85-80	n/a	80, 85	
125W	EC125	940ma	125	

**Electronic Ballasts**

STOCK CODE	Type	Wattage	Power circuit	Current Draw	Dimsn
		VA			mm
PC1/14/21/28/35	Electronic Ballast	1x14,21,28,35	17W	74ma	280x30x21
PC2/14/21/28/35	Electronic Ballast	2x14,21,28,35	33W	143ma	360x30x21
PC2/39T5PRO	Electronic Ballast	2 x 39w	82.5W	354ma	360x30x21
PC2/54T5PRO	Electronic Ballast	2 x 54w	114W	489ma	360x30x21
PC1/18T8PRO	Electronic Ballast	1 X 18w	18.5W	80ma	234x40x28
PC1/36T8PRO	Electronic Ballast	1X 36w	35.5W	150ma	234x40x28
PC1/58T8PRO	Electronic Ballast	1 X 58w	53.5W	230ma	234x40x28
PC2/18T8PRO	Electronic Ballast	2 x 18w	37.5W	80ma	234x40x28
PC1/30T8PRO	Electronic Ballast	1 X 30w	30W	140ma	234x40x28
PC2/30T8PRO	Electronic Ballast	2 x 30w	56W	260ma	234x40x28
PC2/36T8PRO	Electronic Ballast	2 x 36w	71.5W	310ma	234x40x28
PC2/58T8PRO	Electronic Ballast	2 x 58w	108W	460ms	234x40x28
PCA1/30T8ECO	Elec Ballast Dimmable	1X30w	30.1W	135ma	360x30x28
PCA2/30T8ECO	Elec Ballast Dimmable	2X30w	58W	260ma	360x30x28
PCA1/36T8ECO	Elec Ballast Dimmable	1 x 36w	36.5W	165ma	360x30x28
PCA2/36T8ECO	Elec Ballast Dimmable	2 x 36w	70.4W	305ma	360x30x28
EZPLUS 1X36/2X18w	Electronic instant start	1x36/2x18W	36W	160ma	155x42x33
EZPLUS 2X36/4X18w	Electronic instant start	2x36/4x18W	66W	300ma	186x43x33